

VYNCO

PUSH BUTTON TIMER MODULE

220-240Va.c. 50Hz, Max. 1000W



- Min. 30 seconds, Max. 4 hours
- 32 timing intervals



- Ideal for controlling fans, lighting and relays for heating or larger loads.
- Suitable for controlling various types of loads – Incandescent, LED, Fluorescent, small fans, contactors and relays.
- LED indicator on front to show when the Timer is operating.
- 3 Timing modes, 32 Timing intervals.
- Fits all Vynco – Logix, Fusion and Home – Switch Plates.
- Timing range 30 Seconds to 4 hours.
- Timing mode selectable using DIP Switches.



SELECT THE MODE TO PROGRAMME ACCORDING TO HOW YOU WILL USE THE LOAD ATTACHED TO THE TIMER.



Choose **Mode A** if you want to be able to override the timer, even part way through the countdown.

Choose **Mode B** if you want to be able to use the mech as a normal light switch (ON/OFF) as the primary function, but be able to switch on the timer when required.

Choose **Mode C** if you will only ever need to use the attached device on a timer i.e. no override option.

MODE A: TIMER WITH OVERRIDE FUNCTION

1. **Press once** to start the timer. (Press again and the timer will stop and switch off the load.)
2. **Press and hold** for 2 seconds to override the timer, and keep the load active indefinitely.
3. **Press once** again to turn off the load.
4. Next time you press, the timer will start as normal.

Useful for when you know you will need the heater on for longer than what the timer is set for, in one specific situation.

MODE B: ON FUNCTION WITH COUNTDOWN TIMER

1. **Press once** to activate the load, i.e. turn on the light or the fan. The timer has not started.
2. **Press again** and this will start the timer.
3. **Press again** if you need to switch off the load before the timer expires.

Use for bathroom extraction fans, switch the fan on when you are in the shower and set the timer as you leave the bathroom to make sure you don't accidentally leave it on all day.

MODE C: TIMER WITHOUT OVERRIDE FUNCTION

1. **Press once** and this will start the timer.
2. **Press again** if you need to switch off the load before the timer expires.

Use for lighting in areas of low use/short use, where you would be unlikely to ever need the lights on for longer than what you initially set the timer to i.e. walk in pantries or wardrobes, toilets, staircase lighting.

VYNCO INDUSTRIES (NZ) LIMITED

Christchurch Office

388 Tuam Street, Phillipstown, Christchurch 8011
 PO Box 9022, Tower Junction, Christchurch 8149
 New Zealand
P +64 3 379 9283 **F** +64 3 379 6838
E chchsales@vynco.co.nz

[facebook.com/vyncoindustriesltd/](https://www.facebook.com/vyncoindustriesltd/)

Northern Region/Auckland

58 Walls Road, Penrose, Auckland 1061
 PO Box 12 249, Penrose, Auckland 1642
 New Zealand
P +64 9 525 6051 **F** +64 9 525 5799
E vyncoauck@vynco.co.nz

www.vynco.co.nz